

## Verifying trig identities:

Showing that the two sides of the equation really are equal.

Two basic techniques:

- Work on one side only and make it look like the other side.
- or
- Work on both sides until they look the same.

Work on one side only and make it look like the other side.

If you want to work on only one side....which side?

Usually, start with the side that looks more "complicated".

When trying to verify/prove an identity you CAN'T do the following:

- Move terms from one side of the equation to the other side
- Multiply/divide/square/square root both sides of the equation
- Add/Subtract a quantity from both sides of the equation

You are **NOT** solving

You are trying to show the two sides of the equation are equal which means you don't know they are equal....YET.

Verify this identity:

$$1 + \cot A = \csc A (\sin A + \cos A)$$

$$\begin{aligned} 1 + \frac{\cos}{\sin} &= \frac{1}{\sin} (\sin + \cos) \\ \downarrow &\quad \downarrow \\ 1 + \frac{\cos}{\sin} &= 1 + \frac{\cos}{\sin} \end{aligned}$$

Verify this identity:

$$\tan\theta \cdot \sec\theta \cdot \cot\theta = \frac{\tan\theta}{\sin\theta}$$

$$\begin{aligned} \tan\left(\frac{1}{\cos} \cdot \frac{\cos}{\sin}\right) &= \\ \tan\left(\frac{1}{\sin}\right) &= \\ \frac{\tan}{\sin} &= \frac{\tan}{\sin} \end{aligned}$$

Verify this identity:

$$\frac{\sin x}{\tan x} + \frac{\cos x}{\cot x} = \sin x + \cos x$$

$$\frac{\sin}{\frac{\sin}{\cos}} + \frac{\cos}{\frac{\cos}{\sin}} =$$

$$\sin \cdot \frac{\cos}{\sin} + \cos \cdot \frac{\sin}{\cos} =$$

$$\cos + \sin = \sin + \cos$$